

# SP-PAR Q4

## LED WASH



### LED COLOR OUTPUT

- RGBA (REd, Green, Blue, Amber)
  - Red (0-100% brightness)
  - Green (0-100% brightness)
  - Blue (0-100% brightness)
  - Amber (0-100% brightness)

### CONTROL MODES

- DMX Control
- Master/Slave mode
- Auto mode
- Sound-active mode
- Manual color control
- IR remote control

### POWER SAVING & CONTROLS

- Auto-save setting protection
- Display sleep mode after 30 seconds of inactivity

### DMX CHANNEL MODES

- 4CH mode (Red, Green, Blue, Amber)
- 8CH mode (Red, Green, Blue, Amber, Strobe, Programs, Program Speed, Dimmer)

### INTERGRATED FUNCTIONS

- 4-button digital menu navigation
- 15 static preset colors
- 5 Auto & 5 Sound programs with speed/sensitivity adjustments
- Full-range dimmer and variable speed strobe
- Factory reset capability
- IR remote toggling

### PHYSICAL & OPTICAL DESIGN

Features 4 high-output light lenses with a centered IR receiver

