

SP-PAR Q1

LED WASH



CONTROL MODES

- Manual button control
- Auto mode
- Sound-active mode
- IR remote control

INTERGRATED FUNCTIONS

- 2 Auto-run programs via manual switching
- 5 Auto-run programmes via IR remote switching
- 5 Sound control programs via IR remote switching
- Speed adjustment (0 lowest, 9 highest speed)
- Program pause function

STATUS INDICATOR

- Blue indicator light for SOUND mode
- Dual-purpose indicator light (Charging/Power capacity status)

BATTERY CAPACITY MONITORING

- Green: 100%-66% capacity
- Red + Green: 64%-34% capacity
- Red: 33%-11% capacity
- Red flashing: Less than 10% capacity

