

SP-PAR Q6

LED WASH



LED COLOR OUTPUT

- RGBA (Red, Green, Blue, Amber)
 - Red (0–100% brightness)
 - Green (0–100% brightness)
 - Blue (0–100% brightness)
 - Amber (0–100% brightness)

CONTROL MODES

- DMX Control
- Master/Slave mode
- Auto mode
- Sound-active mode
- Manual color control
- IR remote control

POWER SAVING & CONTROLS

- Auto-save setting protection
- Display sleep mode after 30 seconds of inactivity

DMX CHANNEL MODES

- 4CH mode (Red, Green, Blue, Amber)
- 8CH mode (Red, Green, Blue, Amber, Strobe, Programs, Program Speed, Dimmer)

INTERGRATED FUNCTIONS

- 4-button digital menu navigation
- 15 static preset colors
- 5 Auto & 5 Sound programs with speed/sensitivity adjustments
- Full-range dimmer and variable speed strobe
- Factory reset capability
- IR remote toggling

PHYSICAL & OPTICAL DESIGN

Features 6 high-output light lenses with an upper-left offset IR receiver

